




Enhanced energy independence for owners of residential PV systems

- ✓ Optimised energy autonomy
- ✓ Smart and efficient operations
- ✓ Modern and compact design
- ✓ Highest safety standards



Efficient solutions for solar power storage are the key to increased levels of energy autonomy. The EH PLUS+ hybrid inverters are designed to maximise energy output, enhance self-consumption, realise peak-shaving and provide a reliable backup power. Featuring a modern design that does not require fans for cooling, the operation is silent and reliable. An on-grid, battery-ready version of the inverter is available. The EH PLUS+ series is compatible with a range of batteries, including the GoodWe Lynx Home F.

-  High back-up output power
-  UPS level switching <10ms
-  Smart home integration



Technical Data	GW3600N-EH	GW5000N-EH	GW6000N-EH
Battery Input Data			
Battery Type	Li-Ion		
Nominal Battery Voltage (V)	350		
Battery Voltage Range (V)	85 ~ 460		
Max. Continuous Charging Current (A)	25		
Max. Continuous Discharging Current (A)	25		
Max. Charging Power (W)	6000		
Max. Discharging Power (W)	3600	5000	6000
PV String Input Data			
Max. Input Voltage (V)	580		
MPPT Operating Voltage Range (V)	100 ~ 550		
Start-up Voltage (V) ⁴	90		
Nominal Input Voltage (V)	380		
Max. Input Current per MPPT (A)	16		
Max. Short Circuit Current per MPPT (A)	21.2		
Number of MPP Trackers	2		
Number of Strings per MPPT	1		
AC Output Data (On-grid)			
Nominal Apparent Power Output to Utility Grid (VA) ¹	3600	5000	6000
Max. Apparent Power Output to Utility Grid (VA) ¹	3600	5000	6000
Max. Apparent Power from Utility Grid (VA)	7200 (Charging 3.6kW, Backup Output 3.6kW)	10000 (Charging 5kW, Backup Output 5kW)	12000 (Charging 6kW, Backup Output 6kW)
Nominal Output Voltage (V)	230 / 220		
Nominal AC Grid Frequency (Hz)	50 / 60		
Max. AC Current Output to Utility Grid (A)	16	21.7	26.1
Max. AC Current From Utility Grid (A)	32	43.4	52.2
Power Factor	~1 (Adjustable from 0.8 leading to 0.8 lagging)		
Max. Total Harmonic Distortion	<3%		
AC Output Data (Back-up)			
Back-up Nominal Apparent Power (VA)	3600	5000	6000
Max. Output Apparent Power (VA)	3600 (4320@60sec)	5000 (6000@60sec)	6000 (7200@60sec)
Max. Output Current (A)	15.7	21.7	26.1
Nominal Output Voltage (V)	230 (±2%)		
Nominal Output Frequency (Hz)	50 / 60 (±0.2%)		
Output THDv (@Linear Load)	<3%		
Efficiency			
Max. Efficiency	97.6%		
European Efficiency	97.0%		
Max. Battery to AC Efficiency	96.6%		
MPPT Efficiency	99.9%		
Protection			
PV Insulation Resistance Detection	Integrated		
Residual Current Monitoring	Integrated		
Battery Reverse Polarity Protection	Integrated		
Anti-islanding Protection	Integrated		
AC Overcurrent Protection	Integrated		
AC Short Circuit Protection	Integrated		
AC Overvoltage Protection	Integrated		
DC Surge Protection	Type II		
General Data			
Operating Temperature Range (°C)	-25 ~ +60		
Relative Humidity	0 ~ 95%		
Max. Operating Altitude (m)	3000		
Cooling Method	Natural Convection		
User Interface	LED, APP		
Communication with BMS ²	RS485, CAN		
Communication with Meter	RS485		
Communication with Portal	WiFi / Ethernet (Optional)		
Weight (kg)	17		
Dimension (W x H x D mm)	354 x 433 x 147		
Topology	Non-isolated		
Self-consumption at Night (W) ³	<10		
Ingress Protection Rating	IP65		
Mounting Method	Wall Mounted		

*1: The grid feed in power for VDE-AR-N 4105 and NRS097-2-1 is limited 4600VA.

*2: CAN communication is configured by default. If 485 communication is used, please replace the corresponding communication line.

*3: No Back-up Output.

*4: If there is no battery connected, inverter starts feeding into grid only if PV voltage >200V.

*: Please visit GoodWe website for the latest certificates.